
QO200TRNM


QO3100BNF
With Cover Removed

Non-Service Entrance Enclosed Devices
1Ø3W—120/240 Vac—240 Vac—UL Listed

Table 1.98: Enclosed Molded Case Switch, Switch Included, Does NOT provide overcurrent protection

Service		Ampere Rating	General Purpose	Rainproof	Box. No. *[4]*
240 Vac	G B	60 A*[5] [6]*	QO260NATS	QO200TR	2, 9R*[7]*
				QO200TRNM	1NM
				QO260NATR	1R
120/240 Vac	S N	100 A*[8]*	QO2000NS	QO2000NRB	13, 10R

Table 1.99: Enclosed GFCI Circuit Breakers, GFCI Circuit Breaker Included—10 kA Short Circuit Current Rating

Service		Ampere Rating	Type 3R—Rainproof Circuit Breaker Included	Circuit Breaker Only	Box. No. *[4]*
120/240 Vac	S N	50 A	QOE250GFINM	QO250GFI	1NM (Non-metallic) 1R (Metallic)
			HOME250SPA	HOM250GFI	
		60 A	QOE260GFINM	QO260GFI3W	

Table 1.100: 2-Pole Circuit Breaker Enclosures—22 kA Short Circuit Current Rating

Service *[9]*		Ampere Rating	General Purpose *[10]*	Rainproof	Box. No. *[4]*
120/240 Vac	S N	100 A 125 A	QO2100BNF/S QO2125BNF OBS QO2125BNS	QO2100BNRB QO2125BNRB	13, 10R 18, 13R
240 Vac	S N	100 A	QO3100BNF/S	QO3100BNRB	13, 10R
60A Max. Circuit Breaker Enclosures—10 kA Short Circuit Current Rating Circuit breaker not included. Order separately from QO Plug-On Circuit Breakers, page 1-3. Will not accept QO-GFI circuit breaker nor QO circuit breakers with factory-installed accessories.					
240 Vac	G B	60 A*[5]*	—	QO2TR	9R*[7]*

OBS This product is obsolete.

Table 1.101: Q Frame Enclosures and Q Frame Circuit Breakers

Service	Enclosure Only *[11]*			Circuit Breaker (Order Separately)				
	Type 1—General Purpose *[10]*	Type 3R—Rainproof	Box No. *[4]*	Ampere Rating	10 k AIR	25 k AIR	65 k AIR	100 k AIR
S N 2P 240 Vac Maximum	Q22200NS *[12]* or Q23225NF/S	Q22200NRB *[12]* or Q23225NRB	19, 11R 20, 12R	70 A	QBL22070	QDL22070	QGL22070	QJL22070
				80 A	QBL22080	QDL22080	QGL22080	QJL22080
				90 A	QBL22090	QDL22090	QGL22090	QJL22090
				100 A	QBL22100	QDL22100	QGL22100	QJL22100
				110 A	QBL22110	QDL22110	QGL22110	QJL22110
				125 A	QBL22125	QDL22125	QGL22125	QJL22125
				150 A	QBL22150	QDL22150	QGL22150	QJL22150
				175 A	QBL22175	QDL22175	QGL22175	QJL22175
				200 A	QBL22200	QDL22200	QGL22200	QJL22200
				225 A	QBL22225	QDL22225	QGL22225	QJL22225
S N 3P 240 Vac	Q23225NF/S	Q23225NRB	20, 12R	70 A	QBL32070	QDL32070	QGL32070	QJL32070 *[13]*
				80 A	QBL32080	QDL32080	QGL32080	QJL32080 *[13]*
				90 A	QBL32090	QDL32090	QGL32090	QJL32090 *[13]*
				100 A	QBL32100	QDL32100	QGL32100	QJL32100 *[13]*
				110 A	QBL32110	QDL32110	QGL32110	QJL32110 *[13]*
				125 A	QBL32125	QDL32125	QGL32125	QJL32125 *[13]*
				150 A	QBL32150	QDL32150	QGL32150	QJL32150 *[13]*
				175 A	QBL32175	QDL32175	QGL32175	QJL32175 *[13]*
				200 A	QBL32200	QDL32200	QGL32200	QJL32200 *[13]*
				225 A	QBL32225	QDL32225	QGL32225	QJL32225 *[13]*

[4] See Table 1.75 Knockout Information, page 1-33
[5] Not suitable for service equipment.
[6] Maximum 10 hp 240 Vac.
[7] Top endwall has no hub opening.
[8] Maximum 20 hp 240 Vac.
[9] Not for use with one pole QO circuit breakers. Circuit breakers not included. Order QO type circuit breakers separately from pages 1-2 and 1-3. Accepts QO circuit breakers with factory-installed accessories. Order equipment ground bar PKOGTA2, if required.
[10] Order F for flush, S for surface.
[11] Factory-installed groundable neutral assembly includes (2) ground lugs and (2) neutral lugs. Equipment ground kit PKOGTA2 also included.
[12] Accepts 200 A max. 2P Q Frame circuit breakers.
[13] Equipment ground bar kit PKOGTA2 factory-included.

© 2024 Schneider Electric
All Rights Reserved
1/11/2024