BROCHURE

Midwest AC Disconnects



Product features
Technical specification

AC Disconnects
Product features



—
01



—
02

—
01 Fusible and Non-Fusible AC Disconnects

—
02 Non-Fusible AC Disconnects Plus GFCI

Fusible and Non-Fusible AC Disconnects

- Compact size
- Easy installation
- Fusible or non-fusible types
- Noryl thermoplastic or galvanized steel enclosures
- Puller or non-automatic switch type disconnections
- Fusible—UL869 Service Equipment
- Non-Fusible—UL 1429 Enclosed Pullout switch

Non-Fusible AC Disconnects Plus GFCI

- Two styles: puller or non-automatic
- 15A Duplex GFCI receptacle included
- Disconnect switch positioned above GFCI receptacle allows easier access
- On pullout model, handle stores inside enclosure in OFF position
- Large, easy-to-read ON/OFF markings
- Cover conveniently stores in up position
- Padlock ring for extra security



AC Disconnects

Technical specifications

Catalogue No.	Fusing	Phase - Volts	Amps	HP Rating	Cabinet size (in.)
Non metallic					
P035F	Fusible pullout	1-Phase - 120/240V	30 Amp.	3	6 x 8
P065F	Fusible pullout	1-Phase - 120/240V	60 Amp.	10	6 x 8
P065P1	Non-fusible pullout	1-Phase - 120/240V	60 Amp.	10	5 x 7
P065NA1	Non-fusible, non-automatic	1-Phase - 120/240V	60 Amp.	10	5 x 7
Metallic					
U035F2	Fusible pullout	1-Phase - 120/240V	30 Amp.	3	5 x 7
U065F1	Fusible pullout	1-Phase - 120/240V	60 Amp.	10	5 x 9
U0353F	Fusible pullout	3-Phase - 240V	30 Amp.	3-7.5	6 x 14
U0653F	Fusible pullout	3-Phase - 240V	60 Amp.	7.5-15	6 x 14
U065P	Non-fusible pullout	1-Phase - 120/240V	60 Amp.	10	5 x 7
U0653P	Non-fusible pullout	3-Phase - 240V	60 Amp.	7.5-15	6 x 14
U0653P010	Non-fusible pullout	3-Phase - 240V	60 Amp.	7.5-15	7 x 14
U065NA1	Non-fusible, non-automatic	1-Phase - 120/240V	60 Amp.	10	5 x 7
U065NA2	Non-fusible, non-automatic	1-Phase - 120/240V	60 Amp.	10	7 x 10
U035F010	Fusible pullout	1-Phase - 120/240V	30 Amp. with 15 Amp. GFCI receptacle	3	5 x 7
U065F010	Fusible pullout	1-Phase - 120/240V	60 Amp. with 15 Amp. GFCI receptacle	3-10	7 x 9 1/10
U0353F010	Fusible pullout	3-Phase - 240V	30 Amp. with 20 Amp. GFCI receptacle	7.5-15	7 x 14
U0653F010	Fusible pullout	3-Phase - 240V	60 Amp. with 20 Amp. GFCI receptacle	7.5-15	7 x 14
U065P010	Non-fusible pullout	1-Phase - 120/240V	60 Amp. with 15 Amp. GFCI receptacle	10	5 x 7
U0653P010	Non-fusible pullout	3-Phase - 240V	60 Amp. with 20 Amp. GFCI receptacle	7.5-15	7 x 14
U065NA1010	Non-fusible, non-automatic	1-Phase - 120/240V	60 Amp. with 15 Amp. GFCI receptacle	10	5 x 7

ABB Inc.
800 Hymus Boulevard
Saint-Laurent, Quebec
H4S 0B5

new.abb.com/ca/midwest

For more information about Midwest:

Click here

For service:

Contact us

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB Inc. does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of ABB Inc. © 2021 ABB. All rights reserved

Midwest by ABB
The Midwest product line consists of quality and long-lasting weatherproof electrical equipment, proudly made by ABB Inc.